

ANNUNCIATOR (BELL) WIRE

Soft bare copper conductors, thermoplastic insulation.
Multiple conductors are twisted.
105°C, 30 Volts.
RoHS



APPLICATIONS

Single conductors for connecting call bells, buzzer systems, door chimes, etc., on low voltage battery or transformer circuits.
Multi-conductors suitable for furnace controls, etc.

CONSTRUCTION

Solid bare copper; PVC insulation; twisted without fillers.

Annunciation Wire

AWG SIZE	NO. OF CONDS.	INSUL. THICKNESS		NOMINAL O.D.		NET WEIGHT	
		(mm)	(in.)	(mm)	(in.)	kg/km	Ibs/Mft.
18	1	.33	.013	1.91	.075	10.06	6.76
18	2	.33	.013	3.81	.150	20.31	13.65
18	3	.33	.013	4.12	.162	30.47	20.48